You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7. Electrical Parts List

7-1 CS15K5W0X/BWT

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY COVER FRONT	
1	M0001	AA90-03197Z	ASSY COVER FRONT;CS15K5W0X/BWT	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	SC016	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	S.N.A
..2	T0081	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	D-COIL	AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	S.N.A
..2	T0003	AA96-00912H	ASSY COVER P-FRONT;15K5,CIS,HIPS HB,G430	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
...3	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	S.N.A
...3	CIS7	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3	CIS3	AA64-02627D	CABINET FRONT;15K5,HIPS,,,,HB,G4309,SV01	
...3	T0023	AA64-02631A	KNOB-POWER;15K5,ABS HB,G3676,SVM-3012	
...3	T0299	AA64-02632A	WINDOW-RMC,LED;29K5,PC,CLR	
...3	T0022	AA64-02635A	KNOB-CONTROL;29K5,ABS HB,G3676,SVM-3012	
...3	T0057	AA64-70127A	BADGE-BRAND;ALL,AL,T1.4,6.3,L40,SAMSUNG,	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA96-10137B	ASSY SPEAKER;-,8OHM,3W,3001-001020,AA39-	S.N.A
....4	T0082	3001-001020	SPEAKER;3W,8OHM,90DB,140HZ	
....4	T0245	AA39-20505M	LEAD CONNECTOR-ASSY;,4P,350,700MM,YSH025	
...3	T0156	AA61-00721C	HOLDER-RAIL;H4,HIPS,V0,GRAY	S.N.A
			ASSY COVER REAR	
1	M0002	AA90-03198B	ASSY COVER REAR;15K5,RCA6P,FV2,G4309,STE	S.N.A
..2	T0069	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A
..2	T0015	AA64-02628A	CABINET-BACK;15K5,HIPS,FV2,GR503	
..2		AA64-60385B	INLAY-BACK;50.5366,PS,T0.3,-,-,BLK,LINE	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
			ASSY CPT	
1		AA91-06637A	ASSY CPT;CS15K5,15K8,+380MG,A36QDT351X,B	S.N.A
..2		AA91-02166F	ASSY CPT;A36QDT351X,15,+380MG,BARE,CT-1	S.N.A
⚠ ...3	T0063	AA03-00146A	CRT COLOR;A36QDT351X,+380mG,2.5mH,22.5mH	
...3	T0079	AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
...3	T0078	AA27-00161A	DEFLECTION YOKE;15DF,CDY-MT1501A,ST-3,A3	
...3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	S.N.A
..2		AA98-70014G	ASSY TBC WIRE(P);-,15inch,NTSC,1P,KS2A/C	S.N.A
..2	T0089	AA27-00252A	COIL DEGAUSSING;,15INCH,10%,70TS,4.5OHM,	
			ASSY FIXING	
1		AA91-06700A	ASSY FIXING;KS1A,MAC,THE OTHERS,CP2	S.N.A
..2	T0245	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
..2		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A
..2		AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
..2	CLAMP	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
..2		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	S.N.A
⚠ ..2	T0066	AA96-20109B	ASSY POWER CORD;-,CP2/NO(4.0),H/C250,KKP	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3	T0077	AA39-10006X	CBF POWER CORD;-,KKP419C,KLCE-2F,2.286MT	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA61-01364A	HOLDER-COVER;KS1A,NYLON66,BLK,V2	S.N.A
			ASSY CHASSIS	
1	M0017	AA91-06733Z	ASSY CHASSIS;MAC,KS1A	S.N.A
..2	T0091	AA94-08415A	ASSY PCB MISC-PCB A/V SIDE;15K5,KS1A A2	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	JA701	3722-001342	JACK-PIN;1P,3.4MM,NI,YEL,-	
...3	JA702	3722-001343	JACK-PIN;1P,3.4MM,NI,WHT,-	
...3	JA703	3722-001344	JACK-PIN;1P,3.4MM,NI,RED,-	
...3	T0081	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	T0245	AA39-00094A	LEAD CONNECTOR-ASSY;,3(2)P,200MM,YBNH250	
...3	T0245	AA39-20461C	LEAD CONNECTOR-ASSY;,11P,300MM,YBNH250-1	
...3	T0062	AA61-00612E	HOLDER-AV,ASSY;CS15K5,ABS,GRAY,SV-012P S	S.N.A
....4	T0010	AA61-00501C	HOLDER-AV;15X5,ABS HB,G3676,SV012P	S.N.A
....4	T0578	AA64-01431G	INLAY AV;15X5,PS SHEET,T0.3,GRAY,SILVER	S.N.A
...3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
...3		AA97-07264A	ASSY AUTO-A/V SIDE;,KS1A,PAL,15K5,STEREO	S.N.A
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	LE05	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	LE04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	PCB	AA41-00637A	PCB-FRONT AV;CS15K5,FR-1,1L,A,1.6T,245X2	S.N.A
..2	T0073	AA94-13232Z	ASSY PCB MAIN;MAC,KS1A	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	T0090	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
...3	IC112	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
...3	P803T	1404-001265	THERMISTOR-PTC;4.5OHM/100OHM,+30/-20%,22	
...3	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,BK,15X	
⚠ ...3	CR410S	2301-001456	C-FILM,LEAD-OTHER;5.1NF,5%,1.6KV,BK,29X9	
⚠ ...3	CX801S	2306-000318	C-FILM,LEAD-PPF;220NF,20%,250V,BK,-,22.5	
⚠ ...3	CR402S	2306-000350	C-FILM,LEAD-PPF;270NF,5%,400V,BK,26X18.5	
...3	C701	2401-002213	C-AL;150uF,+30-10%,450V,GP,BK,25x35	
⚠ ...3	SW801S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
⚠ ...3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ ...3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
...3	CN906	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
...3	CN906	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
...3	JS701	3722-001138	JACK-PIN;6P,3.4mm,SN,BLK,#16-22	
...3	T0119	AA09-00354A	IC MICOM;TDA9381/N2/3I,SPM-802EEN4,64P,3	
⚠ ...3	T801S	AA26-00134A	TRANS SWITCHING;,CS21S5T,160V~260V,PM2 P	
⚠ ...3	T444S	AA26-00201A	TRANS FBT;FCA173B,KS1A-1,3.8mH,FERRITE,1	
⚠ ...3	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
...3	T0296	AA27-00122A	COIL LINEARITY;90UH,90UH,L81 DR10x10,7.5	
⚠ ...3	LX801S	AA29-30001B	FILTER LINE NOISE;-,-,-,-,27MH,-,-,-,ST,	
...3	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
...3	T0245	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
⚠ ...3	TU01S	AA40-00077A	TUNER;TECC0949PL35A(S),PAL,181CH,38.9MHZ	
...3	GT301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
...3	T0421	AA95-03137A	ASSY SUB PCB-A2,BILINGUAL;20S4,C5,15A9,K	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4	ICS01	1204-002026	IC-SOUND PROCESSOR;MSP3400G-PO-B8-V3,SDI	
....4	CN906	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4	CN906	3711-002708	CONNECTOR-HEADER;NOWALL,10P,1R,2.5mm,ANG	
....4	T0245	AA39-00095A	LEAD CONNECTOR-ASSY;,3(2)P,200MM,YBNH250	
....4	T0245	AA39-00276A	LEAD CONNECTOR-ASSY;,UL1185#26,UL/CSA,6P	
....4		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	XS01	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
....4		AA97-05522A	ASSY AUTO-SUB;14S4,39,KS1A ,A2,BILINGUAL	S.N.A
.....5	ICS02	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	C598	2201-000112	C-CERAMIC,DISC;1.5NF,10%,50V,Y5V,TP,5X3.	
.....5	C598	2201-000180	C-CERAMIC,DISC;10NF,10%,50V,Y5V,TP,7X3MM	
.....5	C598	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C598	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C598	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	
.....5	C598	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	
.....5	C598	2201-000982	C-CERAMIC,DISC;10NF,+80-20%,50V,Y5V,TP,4	
.....5	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C689	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
.....5	C2560	2301-000111	C-FILM,LEAD-PEF;1.8nF,5%,50V,TP,6.5x3.0x	
.....5	C2560	2301-000111	C-FILM,LEAD-PEF;1.8nF,5%,50V,TP,6.5x3.0x	
.....5	C2560	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
.....5	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
.....5	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
.....5	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5	C701	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5	C701	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C701	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C701	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C701	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C701	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
.....5	LS03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
.....5	LS01	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
.....5	LS04	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
.....5	PCB	AA41-00139A	PCB-STEREO/LINE-ST/MTS-M;DREAM-1,1L,FR-1	S.N.A
⚠ ...3	IC801S	AA96-00242D	ASSY H/S;SCREWAA62-30186B,5Q0765RTH,OIL	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	T0086	1203-002916	IC-PWM CONTROLLER;KA5Q0765RTH-YDTU,TO-22	
....4	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	S.N.A
....4	CIS	AA63-30189A	COVER-HEATSINK;-,PC-ABS,T0.8,-,-,V0,NTR,	S.N.A
⚠ ...3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0083	0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0085	1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	S.N.A
....4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
...3	IC301	AA96-00244M	ASSY H/S;SCREWAA64-00046A,LA78040N,OIL S	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	T0088	1204-002121	IC-VERTICAL DEF.;LA78040N,TO220,7P,-,PLA	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4	CIS	AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
⚠ ...3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	S.N.A
....4	T0087	1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
....4	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	S.N.A
...3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	S.N.A
...3	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	S.N.A
....4	T0074	1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
....4	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3		AA97-14208Z	ASSY AUTO;MAC,KS1A	S.N.A
....4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804	0401-000006	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	
....4	T0083	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4	T0083	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001321	DIODE-RECTIFIER;1A4G,400,1A,R-1,TP	
....4	T0083	0402-001321	DIODE-RECTIFIER;1A4G,400,1A,R-1,TP	
....4	T0083	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
....4	T0083	0402-001443	DIODE-RECTIFIER;EGP20K,800V,2A,DO-15,TP	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
....4	DZ016	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ016	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ016	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ016	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0090	0502-000242	TR-POWER;KSA614,PNP,25W,TO-220,TP,40-24	
....4	Q902	0504-001159	TR-DIGITAL;SRC1211M,NPN,400MW,10KOHM,TO-	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R075	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R125	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000645	R-CARBON;330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-001006	R-CARBON;82OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R075	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	R413	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	R827	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R802	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
....4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
....4	R839	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
....4	R838	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
....4	R837	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
....4	R403	2003-001093	R-METAL OXIDE(S);12Kohm,5%,2W,AF,TP,3.9x	
....4	R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
....4	R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
....4	R303	2003-002152	R-METAL OXIDE;1OHM,5%,2W,AG,TP,6X16MM	
....4	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
....4	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
....4	R812	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
....4	R811	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
....4	R024	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
....4	R024	2004-002011	R-METAL(S);110Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R825	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
....4	R814	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
....4	R815	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
....4	R421	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
....4	R505	2008-001135	R-FUSIBLE(S);3.9ohm,5%,1W,AF,TP,3.9x10mm	
....4	C598	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
....4	C598	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
....4	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
....4	C689	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
....4	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C2560	2301-000004	C-FILM,LEAD-PEF;2.2nF,5%,100V,TP,5.5X10X	
....4	C2560	2301-000004	C-FILM,LEAD-PEF;2.2nF,5%,100V,TP,5.5X10X	
....4	C2560	2301-000013	C-FILM,LEAD-PEF;4.7nF,5%,100V,TP,10.5x12	
....4	C2560	2301-000013	C-FILM,LEAD-PEF;4.7nF,5%,100V,TP,10.5x12	
....4	C2560	2301-000016	C-FILM,LEAD-PEF;22nF,5%,100V,TP,7.2x4.5x	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C2560	2301-000016	C-FILM,LEAD-PEF;22nF,5%,100V,TP,7.2x4.5x	
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	C2560	2301-000213	C-FILM,LEAD-PEF;220nF,5%,250V,TP,21.5x11	
....4	C2560	2301-000233	C-FILM,LEAD-PEF;3.9nF,10%,100V,TP,5.8x12	
....4	C2560	2301-000253	C-FILM,LEAD-PEF;39NF,5%,100V,TP,7.5X4.5X	
....4	C2560	2301-000314	C-FILM,LEAD-PEF;8.2nF,5%,50V,TP,6.5x3.0x	
....4	C2560	2301-000314	C-FILM,LEAD-PEF;8.2nF,5%,50V,TP,6.5x3.0x	
....4	C420	2301-001065	C-FILM,LEAD-PPF;47nF,5%,630V,TP,19x15.5x	
....4	C806	2301-001435	C-FILM,LEAD-PPF;1.5nF,5%,1.2kV,TP,15x8x1	
....4	C225	2301-001664	C-FILM,LEAD-OTHER;100nF,3%,50V,TP,20x16x	
....4	C2560	2305-000149	C-FILM,LEAD-PEF;100nF,5%,100V,TP,12x12.5	
....4	C2560	2305-000285	C-FILM,LEAD-PEF;220NF,5%,100V,TP,10.5X5.	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000382	C-FILM,LEAD-PEF;4.7nF,5%,400V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	C701	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
....4	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000481	C-AL;10uF,20%,50V,WT,TP,5x11,5	
....4	C701	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
....4	C701	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
....4	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C701	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
....4	C701	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C701	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	C701	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
....4	C701	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
....4	C701	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
....4	C701	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
....4	C701	2401-001486	C-AL;47uF,20%,160V,HR,TP,13x20mm,5m	
....4	C701	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
....4	C701	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C701	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C701	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C701	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	C701	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	J142	2701-000115	INDUCTOR-AXIAL;10uH,10%,3070	
....4	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	L205	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	L201	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
....4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L701	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L204	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,4514	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	Z202	2903-001240	FILTER-CERAMIC;TR,5.5MHz,-,28dB,-,TP,-	
....4	Z203	2903-001246	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,multi.	
....4	L805	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L803	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	J910	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L801	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L802	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	SW905	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW904	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW903	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW902	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW901	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	CN906	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	FIX02	AA37-00001A	CONNECTOR-FBT FIX PIN;JM-3500,CPTTV,0.36	
....4	FIX01	AA37-00001A	CONNECTOR-FBT FIX PIN;JM-3500,CPTTV,0.36	
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	0	AA41-00849B	PCB MAIN;CS21D8,FR-1,1L,B,1.6T,245*245,M	S.N.A
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P-,PLASTIC,5	
....4	T101	AA26-00025A	TRANS RF;7MG,-,-,-,10pF,-,58.35MHz,7.7x7	
⚠ ...3	SF102S	2904-001024	FILTER-SAW AV;38.9MHz,SIP5K,TP,18.3dB,PA	
⚠ ...3	SF101S	2904-000302	FILTER-SAW AV;38.9MHz,SIP5K,ST,15.4dB,B/	
...3	X901	2801-004033	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	

ASSY P/MATERIAL

1		AA92-05185A	ASSY P/MATERIAL;15K5	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2		6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	S.N.A
..2		6902-000001	BAG AIR;LDPE,T0.2,L1800,W1000,TRP,,LDPE	S.N.A
..2		6902-000004	BAG PE;HDPE/NITRON/HDPE,T0.015/T0.5/T0.0	S.N.A

ASSY ACCESSORY

1	M0017	AA92-05469A	ASSY ACCESSORY;CS15K5WX/BWT,RUSSIA,RUS,K	S.N.A
..2	T0080	AA26-90001C	TRANS MATCHING;-,300ohm/75ohm,PAL,40-890	
..2	T0075	AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-	
..2	T0074	AA59-00198H	REMOCON;,TM59,DREAM,29,L/GRAY,STEREO,NON	
..2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A
..2	T0269	AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
..2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
..2		6902-000009	BAG PE;HDPE,T0.03,L400,W240,TRP,8,2,PE M	S.N.A
..2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
..2	T0563	AA68-01296E	MANUAL USERS;15K2/15K9,RUS,W/P100G,KS1A/	

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-2 CS15K10MA0XXST

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY COVER FRONT	
1	M0001	AA90-04704G	ASSY COVER FRONT;CS15K10MA0XXST	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001268	SCREW-TAPTITE;TH,+,B,M4,L12,ZPC(YEL),SWR	
..2	SC016	AA60-10015A	SCREW-ASSY;-,SWRCH18A,M5,L30,RH,+,WC,-,Z	S.N.A
..2	T0081	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2		AA63-60004K	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,BLK,T2	S.N.A
..2	T0010	AA91-00482A	ASSY HOLDER SPK;-,PP,8ohm/5W,BLK,R(YEL),	
..2	T0003	AA96-01641A	ASSY COVER P-FRONT;15K10,HIPS HB,G4309,S	
...3	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3		AA61-40113A	STOPPER-PCB;501H,HIPS,-,-,HB,NTR,-	S.N.A
...3	CIS7	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3	T0578	AA64-01309H	INLAY AV;PS SHEET,21D8,T0.3,-,-,-,S15A L	S.N.A
...3	T0023	AA64-03449A	KNOB POWER;15,17K10,ABS,HB,G4309,SVM3012	
...3	T0022	AA64-03450A	KNOB CONTROL;15,17K10,ABS,HB,G4309,SVM30	
...3	T0299	AA64-03451A	WINDOW-RMC,LED;17K10,PC,CLEAR	
...3	CIS3	AA64-03492A	CABINET FRONT;15K10,HIPS,HB,G4309,SV012P	S.N.A
...3	T0057	AA64-70127A	BADGE-BRAND;ALL,AL,T1.4,6.3,L40,SAMSUNG,	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3	T0069	AA60-00091G	SPACER-FELT;-,FELT,200X10,-,-,BLK,T0.5,-	S.N.A
..2	T0069	AA60-00091G	SPACER-FELT;-,FELT,200X10,-,-,BLK,T0.5,-	S.N.A
..2		AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	S.N.A
			ASSY CHASSIS	
1	M0017	AA91-06595Z	ASSY CHASSIS;,KS1A	S.N.A
..2	T0073	AA94-13238E	ASSY PCB MAIN;MAC,KS1A	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	T0090	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8-	
⚠ ...3	PC801S	0604-001032	PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	
...3	IC112	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
...3	IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,-,PLASTIC,5	
⚠ ...3	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
...3	P803T	1404-001265	THERMISTOR-PTC;4.5OHM/100OHM,+30/-20%,22	
...3	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,BK,15X	
⚠ ...3	CR410S	2301-001456	C-FILM,LEAD-OTHER;5.1NF,5%,1.6KV,BK,29X9	
⚠ ...3	CX801S	2306-000318	C-FILM,LEAD-PPF;220NF,20%,250V,BK,-,22.5	
⚠ ...3	CR402S	2306-000350	C-FILM,LEAD-PPF;270NF,5%,400V,BK,26X18.5	
...3	C701	2401-003030	C-AL;220uF,20%,450V,GP,BK,30x35,10	
⚠ ...3	SF101S	2904-001143	FILTER-SAW AV;38.9MHz,SIP5K,ST,18dB,B/G,	
⚠ ...3	SF102S	2904-001224	FILTER-SAW AV;38.9MHz,SIP5K,ST,16.3dB,B/	
⚠ ...3	SW801S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
⚠ ...3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ ...3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
...3	CN906	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
...3	JS701	3722-001138	JACK-PIN;6P,3.4mm,SN,BLK,#16-22	
...3	T0119	AA09-00356A	IC MICOM;TDA9381/N2/3I,SPM-802EAN4,64P,3	
⚠ ...3	T801S	AA26-00043A	TRANS SWITCHING;-,-,-,AC90~260V,125/12.5	
⚠ ...3	T444S	AA26-00201A	TRANS FBT;FCA173B,KS1A-1,3.8mH,FERRITE,1	
⚠ ...3	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
...3	T0296	AA27-00122A	COIL LINEARITY;90UH,90UH,L81 DR10x10,7.5	
⚠ ...3	LX801S	AA29-30001D	FILTER LINE NOISE;SQ1913,-,6.0MH,0.8A,-	
...3	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
...3	T0245	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
⚠ ...3	TU01S	AA40-00076A	TUNER;TECC0949PG35A(S),PAL,181CH,38.9MHZ	
...3	GT301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
...3	T0296	AA95-01304A	ASSY ETC-PCB A2 BILINGUAL;,-39,14S4,-D8,	
....4		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4	ICS01	1204-001817	IC-SOUND PROCESSOR;MSP3400D-C5-G4-LH,DIP	
....4	CN906	3711-002706	CONNECTOR-HEADER;NOWALL,8P,1R,2.5mm,ANGL	
....4	CN906	3711-002708	CONNECTOR-HEADER;NOWALL,10P,1R,2.5mm,ANG	
....4	T0245	AA39-00276A	LEAD CONNECTOR-ASSY;,UL1185#26,UL/CSA,6P	
....4	T0245	AA39-20005A	LEAD CONNECTOR-ASSY;,3P,500,YBNH025-03,6	
....4		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
....4		AA97-05522A	ASSY AUTO-SUB;14S4,39,KS1A ,A2,BILINGUAL	S.N.A
.....5	ICS02	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,177MIL,PL	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R125	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	C598	2201-000112	C-CERAMIC,DISC;1.5NF,10%,50V,Y5V,TP,5X3.	
.....5	C598	2201-000180	C-CERAMIC,DISC;10NF,10%,50V,Y5V,TP,7X3MM	
.....5	C598	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C598	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
.....5	C598	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	
.....5	C598	2201-000472	C-CERAMIC,DISC;0.33NF,5%,50V,SL,TP,8.5X3	
.....5	C598	2201-000982	C-CERAMIC,DISC;10NF,+80-20%,50V,Y5V,TP,4	
.....5	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5	C689	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
.....5	C2560	2301-000111	C-FILM,LEAD-PEF;1.8nF,5%,50V,TP,6.5x3.0x	
.....5	C2560	2301-000111	C-FILM,LEAD-PEF;1.8nF,5%,50V,TP,6.5x3.0x	
.....5	C2560	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
.....5	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
.....5	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
.....5	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
.....5	C701	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5	C701	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5	C701	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C701	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
.....5	C701	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C701	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5	C701	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
.....5	LS03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
.....5	LS01	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
.....5	LS04	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
.....5	PCB	AA41-00139A	PCB-STEREO/LINE-ST/MTS-M;DREAM-1,1L,FR-1	S.N.A
....4	XS01	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
⚠ ...3	IC801S	AA96-00242D	ASSY H/S;SCREWAA62-30186B,5Q0765RTH,OIL	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	T0086	1203-002916	IC-PWM CONTROLLER;KA5Q0765RTH-YDTU,TO-22	
....4	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	S.N.A
....4	CIS	AA63-30189A	COVER-HEATSINK;-,PC-ABS,T0.8,-,-,V0,NTR,	S.N.A
⚠ ...3	D806	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0083	0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-	S.N.A
...3	IC601	AA96-00244G	ASSY H/S;-,AUDIO,AA62-00046A,TDA8944J,BR	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	T0085	1201-001741	IC-AUDIO AMP;TDA8944J,DBS,17P,937MIL,DUA	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA61-10162B	BRACKET-IC;-,SBHG-1,T1.0,-,-,-,100	S.N.A
....4		AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
...3	IC301	AA96-00244M	ASSY H/S;SCREWAA64-00046A,LA78040N,OIL S	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	T0088	1204-002121	IC-VERTICAL DEF.;LA78040N,TO220,7P,-,PLA	
....4	T0081	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4	CIS	AA62-00046A	HEAT SINK-PS;-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
...3	IC802	AA96-00245A	ASSY H/S;-,-,AA62-00055A,KA7632,-	S.N.A
....4	T0087	1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-,	S.N.A
...3	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	S.N.A
...3	IC501	AA96-50311A	ASSY H/S;-,VIDEO,AA62-30175D,TDA6107Q,-	S.N.A
....4	T0074	1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
....4	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3		AA97-14170L	ASSY AUTO-MAIN;,KS1A	S.N.A
⚠ 4	D808	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D901	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4	D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D103	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D101	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	T0083	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4	T0083	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
....4	T0083	0402-001321	DIODE-RECTIFIER;1A4G,400,1A,R-1,TP	
....4	T0083	0402-001321	DIODE-RECTIFIER;1A4G,400,1A,R-1,TP	
....4	T0083	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
....4	T0083	0402-001443	DIODE-RECTIFIER;EGP20K,800V,2A,DO-15,TP	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
....4	DZ016	0403-000699	DIODE-ZENER;TZP27B,27V,27-30.8V,1W,DO-41	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
....4	DZ016	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
....4	DZ016	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4	DZ016	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
....4	DZ016	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
....4	DZ016	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ016	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4	T0156	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4	T0090	0502-000242	TR-POWER;KSA614,PNP,25W,TO-220,TP,40-24	
....4	Q902	0504-001159	TR-DIGITAL;SRC1211M,NPN,400MW,10KOHM,TO-	
....4	IC012	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
⚠ 4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R125	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	R125	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-001006	R-CARBON;82OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R075	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001125	R-CARBON(S);300KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R075	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R075	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
....4	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ 4	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
....4	R413	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4	R804	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
....4	R803	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
....4	R827	2003-000998	R-METAL OXIDE;300ohm,5%,2W,AF,TP,3.9x10m	
....4	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
....4	R802	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
....4	R837	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
....4	R838	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
....4	R839	2003-001091	R-METAL OXIDE(S);10ohm,5%,2W,AF,TP,4x12m	
....4	R403	2003-001093	R-METAL OXIDE(S);12Kohm,5%,2W,AF,TP,3.9x	
....4	R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
....4	R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x	
....4	R303	2003-002152	R-METAL OXIDE;1OHM,5%,2W,AG,TP,6X16MM	
....4	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
....4	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
....4	R814	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
....4	R815	2003-002228	R-METAL OXIDE(S);0.47ohm,5%,2W,AG,TP,3.9	
....4	R024	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
....4	R024	2004-001399	R-METAL(S);5.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
....4	R024	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4	R024	2004-002011	R-METAL(S);110Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4	R024	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
....4	R825	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
....4	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
....4	R421	2008-001109	R-FUSIBLE(S);0.18ohm,10%,2W,AG,TP,3.9x12	
....4	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
....4	R505	2008-001135	R-FUSIBLE(S);3.9ohm,5%,1W,AF,TP,3.9x10mm	
....4	C598	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
....4	C598	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
....4	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C598	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
....4	C689	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
....4	C689	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
....4	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4	C2560	2301-000004	C-FILM,LEAD-PEF;2.2nF,5%,100V,TP,5.5X10X	
....4	C2560	2301-000004	C-FILM,LEAD-PEF;2.2nF,5%,100V,TP,5.5X10X	
....4	C2560	2301-000013	C-FILM,LEAD-PEF;4.7nF,5%,100V,TP,10.5x12	
....4	C2560	2301-000013	C-FILM,LEAD-PEF;4.7nF,5%,100V,TP,10.5x12	
....4	C2560	2301-000016	C-FILM,LEAD-PEF;22nF,5%,100V,TP,7.2x4.5x	
....4	C2560	2301-000016	C-FILM,LEAD-PEF;22nF,5%,100V,TP,7.2x4.5x	
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	C2560	2301-000148	C-FILM,LEAD-PEF;10nF,5%,100V,TP,7x3.2x7m	
....4	C2560	2301-000192	C-FILM,LEAD-PEF;1nF,5%,50V,TP,5.3x10mm,5	
....4	C2560	2301-000213	C-FILM,LEAD-PEF;220nF,5%,250V,TP,21.5x11	
....4	C2560	2301-000233	C-FILM,LEAD-PEF;3.9nF,10%,100V,TP,5.8x12	
....4	C2560	2301-000253	C-FILM,LEAD-PEF;39NF,5%,100V,TP,7.5X4.5X	
....4	C2560	2301-000289	C-FILM,LEAD-PEF;5.6nF,5%,50V,TP,7x6x3,5	
....4	C2560	2301-000289	C-FILM,LEAD-PEF;5.6nF,5%,50V,TP,7x6x3,5	
....4	C420	2301-001065	C-FILM,LEAD-PPF;47nF,5%,630V,TP,19x15.5x	
....4	C806	2301-001435	C-FILM,LEAD-PPF;1.5nF,5%,1.2kV,TP,15x8x1	
....4	C2560	2305-000149	C-FILM,LEAD-PEF;100nF,5%,100V,TP,12x12.5	
....4	C2560	2305-000285	C-FILM,LEAD-PEF;220NF,5%,100V,TP,10.5X5.	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000382	C-FILM,LEAD-PEF;4.7nF,5%,400V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
....4	C225	2301-001664	C-FILM,LEAD-OTHER;100nF,3%,50V,TP,20x16x	

Level	Loc. No.	Code No.	Description ; Specification	Remark
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4	C701	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4	C701	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	C701	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
....4	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000481	C-AL;10uF,20%,50V,WT,TP,5x11,5	
....4	C701	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
....4	C701	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
....4	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4	C701	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
....4	C701	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	C701	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	C701	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
....4	C701	2401-001176	C-AL;33uF,20%,25V,GP,TP,5x11,5	
....4	C701	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
....4	C701	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
....4	C701	2401-001486	C-AL;47uF,20%,160V,HR,TP,13x20mm,5m	
....4	C701	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C701	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
....4	C701	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4	C701	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	C701	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
....4	L904	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	J142	2701-000115	INDUCTOR-AXIAL;10uH,10%,3070	
....4	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
....4	L204	2701-000146	INDUCTOR-AXIAL;2.2uH,10%,2534	
....4	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	L205	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	L201	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
....4	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
....4	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
....4	L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L701	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
....4	L203	2701-000197	INDUCTOR-AXIAL;5.6uH,10%,2534	
....4	L101	2701-000202	INDUCTOR-AXIAL;0.56uH,10%,2534	
....4	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,4514	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4	Z201	2903-001239	FILTER-CERAMIC;TR,4.5MHz,-,-0.5dB,TP,-	
....4	Z202	2903-001240	FILTER-CERAMIC;TR,5.5MHz,-,28dB,-,TP,-	
....4	Z203	2903-001246	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,multi.	
....4	L803	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L805	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	J910	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L801	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	L802	3301-000287	BEAD-AXIAL;3.5x1.0x6.0mm,1500,2400G	
....4	SW905	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW904	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW903	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW902	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
....4	SW901	3404-001252	SWITCH-TACT;12VDC,50MA,130GF,7.5X7.1,1	
⚠ 4	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
....4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4	CN906	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4	CN906	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
....4	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	IC063	AA13-20004W	IC HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
....4	T101	AA26-00025A	TRANS RF;7MG,-,-,-,10pF,-,58.35MHz,7.7x7	
....4	FIX02	AA37-00001A	CONNECTOR-FBT FIX PIN;JM-3500,CPTTV,0.36	
....4	FIX01	AA37-00001A	CONNECTOR-FBT FIX PIN;JM-3500,CPTTV,0.36	
....4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4	0	AA41-00849B	PCB MAIN;CS21D8,FR-1,1L,B,1.6T,245*245,M	S.N.A
...3	X901	2801-004033	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
..2	T0091	AA94-13418B	ASSY PCB MISC-A/V SIDE;21D8,KS1A,STEREO	
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	CN906	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	JE601	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
...3	JR01	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
...3	T0245	AA39-20461C	LEAD CONNECTOR-ASSY;,11P,300MM,YBNH250-1	
...3		AA97-14337B	ASSY AUTO;1	S.N.A
....4	R075	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	R075	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4	C689	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
....4	C689	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	LE05	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	LE04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
....4	LE02	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	LE01	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
....4	0	AA41-00567B	PCB-SIDE A/V;CS21D8,FR-1,1L,B,245X245,KS	S.N.A

ASSY CPT

1		AA91-06637A	ASSY CPT;CS15K5,15K8,+380MG,A36QDT351X,B	S.N.A
..2		AA91-02166F	ASSY CPT;A36QDT351X,15,+380MG,BARE,CT-1	S.N.A
⚠ ...3	T0063	AA03-00146A	CRT COLOR;A36QDT351X,+380mG,2.5mH,22.5mH	
...3	T0079	AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
...3	T0078	AA27-00161A	DEFLECTION YOKE;15DF,CDY-MT1501A,ST-3,A3	
...3		AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	S.N.A
..2		AA98-70014G	ASSY TBC WIRE(P);-,15inch,NTSC,1P,KS2A/C	S.N.A
..2	T0089	AA27-00252A	COIL DEGAUSSING;,15INCH,10%,70TS,4.5OHM,	

ASSY P/MATERIAL

1		AA92-07944A	ASSY P/MATERIAL;15K10	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2		6902-000061	BAG AIR;LDPE,T0.2,L1000,W500,TRP,,,	S.N.A
..2		6902-000001	BAG AIR;LDPE,T0.2,L1800,W1000,TRP,,,LDPE	S.N.A
..2		6902-000004	BAG PE;HDPE/NITRON/HDPE,T0.015/T0.5/T0.0	S.N.A

ASSY ACCESSORY

1	M0017	AA92-08070G	ASSY ACCESSORY;,KS1A	S.N.A
..2	T0080	AA26-90002A	TRANS MATCHING;-,75-300ohm,PAL,40-890MHZ	
..2	T0075	AA42-00003A	ANT ROD;-,3S,720mm,ABS,UL/CSA,-	
..2	T0074	AA59-00104M	REMOCON;,TM59,KS2A,29,L/GRAY,NON-TTX,GRA	
..2		AA68-01068B	CARD WARRANTY;-,TSE,W/P120G,-,217*93mm,2	S.N.A
..2	T0563	AA68-01213A	MANUAL USERS;CB5038V,-,THAI/ENG,-,W/P 70	S.N.A
..2	M0432	AA68-01952A	MANUAL-S/D;,ENG,W/P 100(G),ALL1,KS1A	S.N.A
..2		6902-000009	BAG PE;HDPE,T0.03,L400,W240,TRP,8,2,PE M	S.N.A

ASSY FIXING

1		AA91-06496R	ASSY FIXING;KS1A,MAC,THAILAND,CHINA,EP2	S.N.A
..2	T0245	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
..2		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A
..2	CLAMP	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
..2		AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
..2		AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	S.N.A
⚠ ..2	T0066	AA96-20112C	ASSY POWER CORD;-,EP2/NO,H/C250,KJ10,THA	S.N.A
...3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3	T0077	AA39-10006K	CBF POWER CORD;-,KJ-10,SPT-2 2/18AWG,240	
...3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
..2		AA61-01364A	HOLDER-COVER;KS1A,NYLON66,BLK,V2	S.N.A

ASSY COVER REAR

Level	Loc. No.	Code No.	Description ; Specification	Remark
1	M0002	AA90-04706D	ASSY COVER REAR;15K10,HIPS FV2,GR503,RCA	S.N.A
..2	T0069	AA60-00091K	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.35,	S.N.A
..2	T0015	AA64-01369F	CABINET BACK;15A9,HIPS,FV2,GR503	
..2		AA64-60385B	INLAY-BACK;50.5366,PS,T0.3,-,-,BLK,LINE	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

7-3 CB21F102ZSXXEC

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY POWER CORD	
⚠ 1	T0066	AA96-01126A	"ASSY POWER CORD;DP,AA39-10001G,CP2,H/C25	
..2	T0077	AA39-10001G	CBF POWER CORD;-,KKP-419C,KLCE-2F,2.286m	
..2		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
			ASSY CRT	
1		AA94-05859A	ASSY CRT;A51EER31X,+400MG,21	S.N.A
⚠ ..2	T0063	AA03-00279A	CRT COLOR;A51EER33X,+380MG,2.07MH,21.0MH	
..2	T0089	AA27-20003Z	COIL DEGAUSSING;-,21,13.5ohm,25T,L2380,E	
..2		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
..2		AA98-70030A	ASSY TBC WIRE(P);DP,21,AA98-70014C,1P,TV	S.N.A
..2		AA65-30107A	CLAMPER CORE-D,COIL;20~22 INCH,NYLON 66,	S.N.A
			ASSY COVER FRONT	
1	M0001	AA90-04591A	ASSY COVER FRONT;21F10,KS1A	S.N.A
..2	T0081	6002-000515	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(WHT),SWR	
..2	T0081	6002-000515	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(WHT),SWR	
..2	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	SC016	AA60-10050Q	SCREW-ASSY;-,SWRCH18A,M5,L26.5,HH,+,WC,-	S.N.A
..2		AA65-30110A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2	qms	HA83-00052A	LP-TAPE-INK;,WIDTH 55 MM	S.N.A
..2	rating	HA83-00052A	LP-TAPE-INK;,WIDTH 55 MM	S.N.A
..2	T0003	AA96-01490A	ASSY C P-FRONT;21F10,HIPS HB,SILVER,	
...3	CIS3	AA64-03521A	CABINET FRONT;21F10,HIPS,HB,G4309,SV012P	S.N.A
....4		AA81-00106A	A/S-MARKING PAINT;,P432U,DARK GREY,TPC	S.N.A
....4		HA83-00040B	LP-MARKING PAINT;,METALLIC SILVER,SV-012	S.N.A
....4		HA83-00011A	LP-RESIN;,M BATCH,WILSON 6007-GY-60,GRY	S.N.A
....4		HA83-00006A	LP-RESIN HIPS;,BASF495F,NTR,HB	S.N.A
...3	T0022	AA64-03522A	KNOB CONTROL;F10,ABS,HB,G3676,SVM3012	S.N.A
...3	T0023	AA64-03523A	KNOB POWER;F10,ABS,HB,G3676,SVM3012	S.N.A
...3		AA64-03524A	WINDOW REMOCON-LED;F10,PC,CLEAR	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		HA83-00049A	LP-ADHESIVE-HM;12MM,NTR	S.N.A
...3	T0057	AA64-70123B	BADGE-BRAND;ALL,AL,8.5,L50,BLK,SILVER,SA	S.N.A
...3	CIS7	AA61-60003T	SPRING ETC-CS;-,SUS304,-,-,OD7,N5,OD7,-,	S.N.A
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
...3	T0175	AA96-01188A	ASSY SPEAKER P;16OHM,3001-001008,AA39-20	
....4	T0245	AA39-20500G	LEAD CONNECTOR-ASSY;,3(2)P,300MM,67096-0	
....4	T0082	3001-001008	SPEAKER;5W,16ohm,90dB,180Hz	
...3	T0156	HA61-00721B	HOLDER-RAIL;21F5,HIPS,HB,GRY	S.N.A
....4		AA81-00096A	RESIN-A;VL-1823,G5433,A	S.N.A
...3	HRAIL	HA83-00049A	LP-ADHESIVE-HM;12MM,NTR	S.N.A
..2	T0010	AA61-01314A	HOLDER-AV;20F10,HIPS,G4309,SV012P,HB	
..2	T0081	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
			ASSY COVER REAR	
1	M0002	AA90-04456A	ASSY COVER REAR;21F3,SEH	S.N.A
..2	T0015	AA64-03006A	CABINET-BACK;21F3,HIPS,FV2,GR503	
...3		AA81-00096A	RESIN-A;VL-1823,G5433,A	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
..2		AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
			ASSY ACCESSORY	
1	M0017	AA94-05765A	ASSY ACCESSORY;20-21,KS1A,XEC	S.N.A
..2		HA68-02125A	LABEL;A/P120(G),70,69,ALLXEC,BLAC	
..2		HA83-00047A	LP-TAPEACETATE;T0.1MM,W20MM,L200MM	S.N.A
..2		HA68-00336B	CARD-WARRANTY;A/P100(G),A5,NEW VERSION,I	S.N.A
			ASSY PCB MAIN	
1	T0073	AA94-13635A	ASSY PCB MAIN;CB21F5Z,21F5,KS1A	
..2	PCB(AC	AA97-13991A	ASSY AUTO;CB21F5,21F5,KS1A	S.N.A
...3	D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...3	D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...3	T0083	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
...3	T0083	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
...3	T0083	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
...3	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
...3	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
...3	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
...3	T0083	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
...3	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
...3	T0083	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
...3	T0083	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
...3	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
...3	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
...3	DZ016	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
...3	DZ016	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
...3	DZ016	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
...3	DZ016	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
...3	DZ016	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
...3	DZ016	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
...3	DZ016	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
...3	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
...3	DZ016	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
...3	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	T0156	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
...3	T0156	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
...3	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
...3	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
...3	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
...3	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
...3	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
...3	T0156	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
⚠ ...3	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
...3	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
...3	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
...3	R125	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
...3	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
...3	R075	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
...3	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3	R075	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3	R075	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3	R075	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
...3	R125	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R125	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	R075	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
...3	R075	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	R075	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	R075	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	R075	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
...3	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
...3	R075	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
...3	R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
...3	R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
...3	R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
⚠ ...3	RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ ...3	RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
...3	R827	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
...3	R316	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
...3	R315	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
...3	R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
...3	R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
...3	R303	2008-001133	R-FUSIBLE(S);0.75ohm,5%,2W,AF,TP,3.9x10m	
...3	R801	2003-002171	R-METAL OXIDE(S);150ohm,5%,2W,AG,TP,3.9x	
...3	R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
...3	R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
...3	R024	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
...3	R024	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
...3	R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
...3	R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
...3	R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
...3	R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
...3	R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
...3	R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
...3	C598	2201-000180	C-CERAMIC,DISC;10NF,10%,50V,Y5V,TP,7X3MM	
...3	C598	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
...3	C598	2201-000259	C-CERAMIC,DISC;0.18NF,10%,500V,Y5P,TP,5.	
...3	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
...3	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
...3	C598	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
...3	C598	2201-000573	C-CERAMIC,DISC;0.047NF,5%,50V,C0G,TP,5X3	
...3	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
...3	C598	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
...3	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
...3	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
...3	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
...3	C598	2201-000991	C-CERAMIC,DISC;0.56NF,10%,2KV,Y5P,TP,7.5	
...3	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
...3	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
...3	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
...3	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
...3	C689	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
...3	C689	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
...3	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
...3	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
...3	C689	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
...3	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
...3	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
...3	C689	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
...3	C689	2202-000825	C-CERAMIC,MLC-AXIAL;680pF,10%,50V,Y5P,TP	
...3	C689	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T	
...3	C2560	2301-000204	C-FILM,LEAD-PEF;2.7nF,5%,50V,TP,7.4x3.9x	
...3	C2560	2301-000213	C-FILM,LEAD-PEF;220nF,5%,250V,TP,21.5x11	

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	C2560	2301-000224	C-FILM,LEAD-PEF;22nF,5%,50V,TP,7.4x3.9x1	
...3	C2560	2301-000224	C-FILM,LEAD-PEF;22nF,5%,50V,TP,7.4x3.9x1	
...3	C2560	2301-000235	C-FILM,LEAD-PEF;3.9nF,5%,50V,TP,6.5x3.0x	
...3	C2560	2301-000254	C-FILM,LEAD-PEF;39nF,5%,50V,TP,7.5x3.5x6	
...3	C2560	2301-000111	C-FILM,LEAD-PEF;1.8nF,5%,50V,TP,6.5x3.0x	
...3	C2560	2301-000342	C-FILM,LEAD-PEF;2.2nF,5%,50V,TP,7.4x3.9x	
...3	C2560	2301-000342	C-FILM,LEAD-PEF;2.2nF,5%,50V,TP,7.4x3.9x	
...3	C2560	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
...3	C2560	2301-000445	C-FILM,LEAD-PEF;4.7nF,5%,50V,TP,5.5x7x3m	
...3	C2560	2301-000445	C-FILM,LEAD-PEF;4.7nF,5%,50V,TP,5.5x7x3m	
...3	C420	2301-001065	C-FILM,LEAD-PPF;47nF,5%,630V,TP,19x15.5x	
...3	C806	2301-001435	C-FILM,LEAD-PPF;1.5nF,5%,1.2kV,TP,15x8x1	
...3	C2560	2305-000285	C-FILM,LEAD-PEF;220NF,5%,100V,TP,10.5X5.	
...3	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000289	C-FILM,LEAD-PEF;220nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000382	C-FILM,LEAD-PEF;4.7nF,5%,400V,TP,-.5mm	
...3	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-.5mm	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C2560	2305-000665	C-FILM,LEAD-PEF;100nF,5%,63V,TP,7.5x4.0x	
...3	C225	2301-001664	C-FILM,MPE-PPF;100nF,3%,50V,TP,20x16x8.5	
...3	C701	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
...3	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
...3	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
...3	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
...3	C701	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
...3	C701	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
...3	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
...3	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
...3	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
...3	C701	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
...3	C701	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
...3	C701	2401-000603	C-AL;1UF,20%,50V,GP,TP,5X11,2	
...3	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
...3	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
...3	C701	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
...3	C701	2401-000758	C-AL;0.22UF,20%,50V,GP,TP,5X11,5	
...3	C701	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
...3	C701	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
...3	C701	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
...3	C701	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	C701	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
...3	C701	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
...3	C701	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
...3	C701	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
...3	C701	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
...3	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
...3	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
...3	C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
...3	C701	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
...3	C701	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
...3	C701	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
...3	C701	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
...3	L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
...3	L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
...3	L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
...3	L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
...3	L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2534	
...3	L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2534	
...3	L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
...3	L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
...3	L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
...3	L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
...3	L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
...3	L204	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2534	
...3	L902	2701-000180	INDUCTOR-AXIAL;33uH,5%,2534	
...3	L904	2701-000180	INDUCTOR-AXIAL;33uH,5%,2534	
...3	L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
...3	L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
...3	L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
...3	L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2534	
...3	X901	2801-003937	CRYSTAL-UNIT;12MHz,25ppm,28-AAM,30pF,30o	
...3	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
...3	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
...3	F101	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
...3	Z202	2903-001040	FILTER-CERAMIC;TR,5.5/6.0/6.5MHz,-,1dB,-	
...3	J910	3301-000287	BEAD-AXIAL;,3.5x1.0x6.0mm,3000mA,TP,,,50	
...3	L802	3301-000287	BEAD-AXIAL;,3.5x1.0x6.0mm,3000mA,TP,,,50	
...3	L803	3301-000287	BEAD-AXIAL;,3.5x1.0x6.0mm,3000mA,TP,,,50	
...3	SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
...3	SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
...3	SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
...3	SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
...3	SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ ...3	FD801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
...3	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
...3	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
...3	PCB	AA41-00131H	PCB-MAIN;CS21D8,FR-1,1L,H,1.6T,245X245,K	S.N.A
...3	EY101	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY501	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...3	EL301	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL302	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL501	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL502	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL601	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL602	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL603	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL604	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
...3	GT101	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	GT807	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
...3	R421	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
...3	L101	2701-000171	INDUCTOR-AXIAL;0.33uH,10%,2534	
...3	IC063	AA13-20004W	IC HYBRID;-,PAP103T,SIP,6P,PRE-AMP,TP	
...3	RW701	2011-001133	R-NET;33K/24K/75x3,5%,1/8W,X,SIP,6P,	
...3	R814	2008-001112	R-FUSIBLE(S);2.4ohm,5%,2W,AG,TP,3.9x12mm	
...3	R815	2008-001112	R-FUSIBLE(S);2.4ohm,5%,2W,AG,TP,3.9x12mm	
...3	R505	2008-001013	R-FUSIBLE(S);1.2ohm,5%,2W,AF,TP,3.9x10mm	
...3	R125	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	L807	2701-001030	INDUCTOR-AXIAL;43uH,10%,4514	
...3	L804	2701-001030	INDUCTOR-AXIAL;43uH,10%,4514	
...3	C689	2202-000253	C-CERAMIC,MLC-AXIAL;4.7nF,20%,16V,Y5R,TP	
...3	C701	2401-000711	C-AL;2200uF,20%,25V,GP,TP,16x25,7.5	
⚠ ...3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
...3	R024	2004-004969	R-METAL(S);1.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
...3	R075	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	
...3	R075	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
⚠ ...3	D804	0401-000006	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	
...3	T0083	0402-001470	DIODE-RECTIFIER;RU2BV1,800V,1A,DO-204AC,	
...3	R075	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3	C701	2401-002462	C-AL;33uF,20%,16V,GP,TP,5x11,5	
...3	R024	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
...3	R811	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
...3	R812	2003-002239	R-METAL OXIDE(S);100KOHM,5%,2W,AF,TP,3.9	
...3	R413	2003-001035	R-METAL OXIDE(S);27ohm,5%,2W,AF,TP,3.9x1	
...3	C701	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5	
...3	R075	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
...3	C701	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
...3	C701	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
...3	R125	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	R125	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
...3	C2560	2301-000247	C-FILM,LEAD-PEF;33nF,5%,50V,TP,8.1x4.5x1	
...3	C689	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
...3	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
...3	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
...3	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
...3	DZ016	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-,	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
...3	M0125	BH39-40362W	CBF-HARNESS;-,JUMPER,0.6PHI,ROLL-TYPE,-	S.N.A
⚠ ..2	NT802S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
..2	P803T	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ ..2	CX801S	2306-000318	C-FILM,LEAD-PPF;220NF,20%,250V,BK,-,22.5	
⚠ ..2	SF101S	2904-001070	FILTER-SAW AV;38.9MHz,SIP5K,TP,14.6dB,B/	
⚠ ..2	T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,-,-,7.1mH,-,-,102uH,	
⚠ ..2	LX801S	AA29-30001D	FILTER LINE NOISE;SQ1913,-,6.0MH,0.8A,-	
⚠ ..2	TU01S	AA40-00076A	TUNER;TECC0949PG35A(S),PAL,181CH,38.	
..2	LD901	AA96-00555A	ASSY LED GUIDE;-,-,UEX-LD-030,GREEN	S.N.A
..2	IC501	AA96-00842A	ASSY H/S;,VIDEO,AA62-30175D,TDA6107Q	S.N.A
...3	T0074	1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	
...3	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
...3	H/S501	AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
⚠ ..2	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
..2	RM901	AA32-00015A	MODULE REMOCON;FRP-3521H31,38KHZ,940MM,M	
⚠ ..2	IC801S	AA96-00845A	ASSY H/S;,POWER,AA62-30186B,KA5Q0765R	S.N.A
...3	T0086	1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
...3	T0081	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3	H/S801	AA62-30186B	HEAT SINK-ES;-,-,-,SILVER,171J + COVER-H	S.N.A
...3		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ..2	IC802	AA96-00846A	ASSY H/S;,POWER,AA62-00055A,KA7632	S.N.A
...3	T0087	1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	
...3	H/S802	AA62-00055A	HEAT SINK-PS;-,-,T1.0,-,35*15*25,D1,-,-	S.N.A
...3	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
..2	IC112	1103-001106	IC-EEPROM;C81DC,1028x8Bit,DIP,8P,300MIL,	
⚠ ..2	SW801S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
..2	T0090	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8	
..2	JS701	3722-000183	JACK-SCART;21P,4mm,SN,BLK,NO	
..2	T0245	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
..2	T0245	AA39-20010D	LEAD CONNECTOR-ASSY;,1P,400,YFH800-01,S,	
..2	T0245	AA39-20620C	LEAD CONNECTOR-ASSY;,9P,500MM,YBNH250-09	
..2	IC301	AA96-00847A	ASSY H/S;,AA62-00046A,LA7840	S.N.A
...3	T0088	1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	
...3		AA62-00064A	HEAT SINK-PS;DP,-,-,-,AA62-00046A,-,-,-,	S.N.A
...3	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
...3		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
..2	C701	2401-000534	C-AL;150uF,20%,400V,GP,ST,25x30,10	
⚠ ..2	CR402S	2306-000350	C-FILM,LEAD-PPF;270NF,5%,400V,BK,26X18.5	
⚠ ..2	T444S	AA26-00116A	TRANS FBT;FSV-14A004H(S),CT15A8,3.24MH,1	
..2	CIS1	AA98-00079A	ASSY SUB PART;KS1A,MAIN(OPT),PAL,-	S.N.A
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2	T0296	AA27-30001B	COIL LINEARITY;-,195uH,QIC1010,PI0.4,4.5	
⚠ ..2	CR410S	2303-001015	C-FILM,LEAD-PPF;5.5NF,5%,1.6KV,BK,29X9.5	
..2	IC602	AA96-00848A	ASSY H/S;,SOUND,AA62-30175D,TDA8943	S.N.A
...3	T0081	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
...3	H/S602	AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	T0085	1201-001740	IC-AUDIO AMP;TDA8943,SIL,9P,850MIL,SINGL	
..2	CN906	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH	
..2	CN906	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
..2	LW01	AA27-40001M	COIL HORIZ. WIDTH;-,180/480uH,SB-5S6202.	
..2	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,BK,15X	
..2	T0119	AA09-00362A	IC MICOM;TDA9381/N2/3I,SPM-802EWN4,64P,	
⚠ ..2	T801S	AA26-00134A	TRANS SWITCHING;,CS21S5T,160V~260V,PM2 P	
..2	CN401	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
..2	C1	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A
..2	C2	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A
..2	C3	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A

ASSY P/MATERIAL

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA92-07738A	ASSY P/MATERIAL;21F10	S.N.A
..2		AA69-00744E	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1300,H1	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
...3		HA83-00058A	LP-RESIN-EPS;,CHEIL SF-301V,WHT	S.N.A
..2	acc-ba	HA83-00047A	LP-TAPEACETATE;T0.1MM,W20MM,L200MM	S.N.A

ASSY PCB MISC-A/V SIDE

Level	Loc. No.	Code No.	Description ; Specification	Remark
1	T0091	AA98-02243A	ASSY PCB MISC-A/V SIDE;21F10,PAL	S.N.A
..2	JE601	3722-000144	JACK-PHONE;6P/5C,3.6PI,MBAG,BLACK,-	
..2	JA701	3722-001041	JACK-PIN;1P,3.4mm,#16-22,AU	
..2	JA702	3722-001042	JACK-PIN;1P,3.4mm,#16-22,AU	
..2	T0245	AA39-20112E	LEAD CONNECTOR-ASSY;,9P,300,YBNH025-09,6	
..2		AA97-14324A	ASSY AUTO-A/V SIDE;21F10,KS1A	S.N.A
...3	R075	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
...3	C689	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
...3	C689	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
...3	C701	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
...3	LE04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2534	
...3	LE01	2701-000159	INDUCTOR-AXIAL;22uH,10%,4298	
...3	0	AA41-00918A	PCB-USB;CS21F10,FR-1,1L,A,1.6T,245*245,K	S.N.A
..2		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A

Level	Loc. No.	Code No.	Description ; Specification	Remark

Level	Loc. No.	Code No.	Description ; Specification	Remark